

Disable SELinux and Firewall on CentOS 7

Disable SELinux

Reboot is needed to disable SELinux.

Check the status of SELinux

```
sestatus
```

Disable SELinux Temporarily

```
echo 0 > /selinux/enforce
```

or

```
setenforce 0
```

Disable SELinux Permanently

/etc/sysconfig/selinux

```
SELINUX=disabled
```

Disable Firewall

Check the status of firewall

```
systemctl status firewalld
```

Stop and disable firewall

```
systemctl stop firewalld  
systemctl disable firewalld
```

Remove netfilter rules

```
iptables -t filter -F  
iptables -t nat -F  
iptables -t mangle -F
```